

High Performance Test Cable Assemblies

FPT-50

Phase & Loss Stable, Long Flex Life

Features:

- Low insertion loss
- High Phase Stability
- High Power
- High Durability

Applications:

- Laboratory Test
- Avionics
- Phased-array Radar
- Satellite Communication

Electrical

Frequency	DC-50GHz
Impedence	50Ω
Impedance	50Ω
Velocity of Propagation	76%
Shielding Effectiveness	90dB Min.
Voltage Withstand	500V DC
Phase Stability ^[1]	±7°
Amplitude Stability ^[1]	±0.05dB

[1] 50mm radius, 360° bending

Mechanical

Unarmored Bend Radius (installation/repeated)	18mm/36mm Min.
Armored Bend Radius (installation/repeated)	30mm/60mm Min.
Bending Life Cycle	100,000

[2] For connectors 2.4mm, 2.92mm, 3.5mm, SMA, N only.

Environmental

Temperature	-55 ~ +165°C
-------------	--------------

Construction



1	2	3	4	5	6	7	8	9	10
---	---	---	---	---	---	---	---	---	----

No	Name	Size (mm)	Material
1	Inner Conductor	0.72	Silver-plated copper
2	Dielectric	2.1	Low density PTFE
3	Inner Shield	2.25	Silver-plated copper tape
4	Interlayer	2.55	Low density PTFE
5	Outer Shield	3.01	Silver-plated copper braid
6	Jacket	3.60	FEP
7~9	Aarmor (optional)	5.50	Composite
10		6.00	PTFE

Tolerance: ±0.02mm[±0.008in]

Attenuation & Power Handling

Frequency (GHz)	1	2	3	6	8	10	12.4	18	26.5	40	50
Attenuation ^[2] (dB/100m)	48.1	68.3	83.9	119.4	138.4	155.2	173.4	210.2	257.1	319.2	359.2
Average Power ^[3] (W)	506	356	290	204	176	157	140	116	95	76	68

[2] VSWR: 1.0; Ambient: +25°C (77°F); Raw cable

[3] VSWR: 1.0; Ambient: +40°C (104°F); Sea level

Calculate Cable Attenuation: Attenuation (dB/100m) = $1507808 * \sqrt{F (MHz)} + 0.000440 * F (MHz)$

Calculate Connector Attenuation: Attenuation (dB/100m) = $0.03 * \sqrt{F (GHz)}$